



## Balanced RCA Adapter Specs



<b>Model</b>	BXLR3M10
<b>Overview</b>	Balanced RCA to XLR-3 Male Cable
<b>Highlights</b>	Conductor: 6N OCC Single Crystal Copper Insulation: PVC insulation for each conductor Shielding: Oxygen-Free Copper, Braided
<b>Tech Specs</b>	<b>Connectors:</b> Neutrik XLR-3 Male (NC3MXX-HE, Gold Contacts) Khadas Balanced RCA Plug (KRP-B01) <b>Cable:</b> Length: 1.0 m OCC Purity: 6N (99.9999%)
<b>Cable Specs</b>	<b>Wires:</b> Conductor: 4x 0.18 mm + 50x 0.10 mm; OCC (Twisted Pair) Red Conductor: 4x 0.18 mm + 50x 0.10 mm; OCC (Twisted Pair) White Conductor: 4x 0.18 mm + 50x 0.10 mm; OCC Orange PVC insulation for each conductor OCC Purity: 6N (99.9999%) <b>Insulation:</b> Shielding: 112x 0.10 mm; Oxygen-free Copper, Braided Filler: Cotton Yarn Inner Jacket: PVC with KHADAS Logo Outer Jacket: Black Braided Cloth Outer Diameter: 6.0 mm
<b>Compatibility</b>	Tone2 Pro Tone2
<b>In the Box</b>	1x Khadas BXLR3M Cable (Red) 1x Khadas BXLR3M Cable (White)