

3705 Cooling Fan

Model

KFAN3705

Overview

Slim & High-speed Cooling Fan

The 3705 Cooling Fan and New VIMs Heatsink Kit are designed for best possible cooling performance when you use VIMs SBC boards. It's easy to setup and with good looking, it's the best solution for VIMs to remain stable under high clocks.

Highlights

Slim & High-speed

Super Quiet

New VIMs Heatsink mountable

Tech Specs

Rated Voltage 5.0 VDC
Starting Voltage 4.5 VDC

Operating Voltage 4.5 ~ 5.5 VDC

Cosuming Current Nominal 0.150A

Max. 0.163A

Cosuming Power Nominal 0.750A

Max. 0.815A

Rotation Speed (RPM) Min. 9540

Nominal 10600 Max. 11550

Sould Level (50cm): Nominal 45dB(A)

Max. 51dB(A)

 $\begin{array}{ccc} \text{Max. Airflow} & & \text{Min.} & \text{1.06CFM} \\ & \text{Nominal} & \text{1.48CFM} \end{array}$ $\text{Max. Static Pressure} & & \text{Min.} & \text{137Pa} \end{array}$

Nominal 178Pa

Direction of Rotation CCW

Operating Temperature: -10°C ~+ 70°C

Operating Humidity: ~90%RH

Lines: White: TACH, Black: GND, Gray: PWM, Red: +V

Header: 4Pins, 0.8mm Pitch

Weight:

8.6g

Dimensions:

37.0 * 37.0 * 5.9mm

Documents

 $Specifications: https://dl.khadas.com/Hardware/Accessories/Fan/Fan3705_Specification.pdf$

New VIMs Heatsink

3D CAD File: https://dl.khadas.com/Hardware/Accessories/Fan/Fan3705_3D_CAD.zip

Compatibility Khadas VIM1 (V1.4)

Khadas VIM2 (V1.4) Edge Heatsink
Khadas VIM3 Khadas DIY Case

Khadas VIM3L Khadas Edge-V Khadas Edge

In the Box

3705 Cooling Fan

Screw Sets